H+M 300 - LED module



Complete LED module for easy and efficient refurbishment of existing **H+M Ø300** variants for surface mount or recession.

LED and driver spec:

LED type: 244 mm board, 11 or 15 W

Operational life: min 50,000 hours at ta 25°C, L80B10

Colour temperature: 2700, 3000, or 4000 Kelvin

alternatively 2700-6500 K dynamic

Energy eff. class: 2700 K: E - 3000, 4000, 6500 K: D

Colour rendering: min 90 Ra Colour accuracy: 3 steps SDCM

Driver: 20 W LED driver, dimming optional

Operational life: min 50,000 hours

Exchange of lamp module: Recessed fixtures:

Demounting:

Old fixtures (3 cm visible height): Pull off the outer ring downwards. Revised fixtures (2 cm visible height): Turn collar and shade off as one unit anti-clockwise.

Unfasten the old lamp by demounting cables and plate (2 screws). Fasten the new LED module by the existing screws, connect the cables and clips on the LED board.

Remount/Turn the bottom part clockwise into locked position again.



The shade is unfixed and can be removed by tipping it upwards in one side.

Unfasten the old lamp by demounting cables and plate (2 screws). Fasten the new LED module by the existing screws, connect the cables and clips on the LED board.

Replace the shade.

We include a blank lable in the consignment. Write the old item number on the lable and attach it inside the luminaire.



Variants:

LED module fo	r H+M	Ø300 mm, surfa	ce mo	unt or recesse	d					
Item No.	Lamp type			Select colour temperature and other options in the table below.						
1901-	H+M 300, 11 W, 350 mA									
1902-	H+M 300, 15 W, 500 mA									
Combine with:	Colour temperature			Dimming						
	927	2700 K, 90 Ra	V	1-10 V						
	930	3000 K, 90 Ra	D	Dali						
	940	4000 K, 90 Ra								
	9WD	TW, Dali, 90 Ra								
Fuamula:	1001	0200 11WIFD	د ماییام ۲	000 I/ 00 Da Dali						
Example:	1901-930D = 11 W LED module, 3000 K, 90 Ra, Dali									
The above LED	modu	les fit the follow	ing vai	riants (X stand	s for colo	ır code):				
	2051, 2151, 254X, 264X									
	2005X, 2105X, 2205X, 2305X, 2805X, 2114X, 2214X, 2314X, 2814X									
	2860	, 2861, 2870, 2871								
	Pleas	e take contact if yo	ur item	number is not	in the list.					